



— DGS-712

1000BASE-T Copper SFP Transceiver

Gigabit Transmission on Cat. 5 Twisted-Pair Cable

The D-Link DGS-712 1000BASE-T Copper Small Form Pluggable (SFP) transceiver is based on the SFP Multi Source Agreement (MSA). It is compatible with the Gigabit Ethernet and 1000BASE-T standards as specified in IEEE Std 802.3z and IEEE Std 802.3ab. The 1000BASE-T physical layer IC (PHY) can be accessed via I2C, allowing access to all PHY settings and features.

The DGS-712 1000BASE-T copper SFP transceiver plugs into an SFP slot provided for on a D-Link Gigabit switch or optional switch module. It provides Gigabit transmission on the common Category 5 twisted-pair network cable.

Key Features

- Up to 1.25Gb/s bi-directional data links
- Hot-pluggable SFP footprint
- Extended case temperature range
- Fully metallic enclosure for low EMI
- Low power dissipation (typical 1.2 watts)
- RJ-45 connector assembly
- Access to physical layer IC via 2-wire serial bus
- 10/100/1000 BASE-T operation in host systems with SGMII interface
- Gigabit Ethernet over Cat. 5 cable
- +3.3V electrical power interface

DGS-712

Technical Specifications

Transceiver

Standard

IEEE 802.3ab 1000BASE-T Gigabit Ethernet

Transceiver Type

SFP (Small Form Pluggable)

Connector

RJ-45

Auto MDI/MDIX

- Automatic crossover detection enabled
- External crossover cable not required

Data Rate

- 1,000 Mbps (IEEE 802.3 compatible)
- 10/100/1000 BASE-T operation requires the host system to have an SGMII interface with no clocks. With a SERDES interface, this transceiver will operate at 1000BASE-T only.

Cable Type

Cat. 5 twisted-pair cable

Maximum Cable Distance Coverage

100 meters

Supply Current

- 350mA (typical)
- 400mA (maximum)
- 1.3W max power over full range of voltage and temperature *

* Caution: power consumption and surge current are higher than the specified values in the SFP MSA

Input Voltage

- 3.1V (minimum)
- 3.3V (typical)
- 3.5V (maximum)
- Referenced to GND

Maximum Voltage

4V

Surge Current

- 30mA
- Hot plug above steady state current *

* Caution: power consumption and surge current are higher than the specified values in the SFP MSA

Operating Temperature

0° to 85 °C

Storage Temperature

-40° to 85 °C



Ordering Information

DGS-712 1000BASE-T Copper SFP Transceiver



Specifications subject to change without prior notice.
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A	TEL: 1-714-885-6000	FAX: 1-866-743-4905
Canada	TEL: 1-905-8295033	FAX: 1-905-8295223
Europe	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
Germany	TEL: 49-6196-77990	FAX: 49-6196-7799300
France	TEL: 33-1-30238688	FAX: 33-1-30238689
Netherlands	TEL: 31-10-282-1445	FAX: 31-10-282-1331
Belgium	TEL: 32(0)2-517-7111	FAX: 32(0)2-517-6500
Italy	TEL: 39-2-2900-0676	FAX: 39-2-2900-1723
Iberia	TEL: 34-93-4090770	FAX: 34-93-4910795
Sweden	TEL: 46-(0)8564-61900	FAX: 46-(0)8564-61901
Norway	TEL: 47-23-897189	FAX: 47-22-309085
Denmark	TEL: 45-43-969040	FAX: 45-43-424347
Finland	TEL: 358-9-2707-5080	FAX: 358-9-2707-5081
Singapore	TEL: 65-6774-6233	FAX: 65-6774-6322
Australia	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
China	TEL: 86-10-5863-5800	FAX: 86-10-5863-5799
India	TEL: 91-022-2652-6696	FAX: 91-022-2652-8914
Middle East (Dubai)	TEL: 9714-3916480	FAX: 9714-3908881
Turkey	TEL: 90-212-335-2553	FAX: 90-212-335-2500
Egypt	TEL: 202-414-4295	FAX: 202-415-6704
Israel	TEL: 972-9-9715700	FAX: 972-9-9715601
Latin America	TEL: 56-2-232-3185	FAX: 56-2-232-0923
Brasil	TEL: 55-11-55039320	FAX: 55-11-55039322
South Africa	TEL: 27-1266-52165	FAX: 27-1266-52186
Russia	TEL: 7-095-744-0099	FAX: 7-095-744-0099#350
Taiwan	TEL: 886-2-2910-2626	FAX: 886-2-2910-1515
D-Link Corp.	TEL: 886-2-2916-1600	FAX: 886-2-2914-6299